

For Light Series - LED3000/LED3001

******Proper installation of this product is the sole responsibility of the installer******

INSTALLATION:

1. Locate a flat surface on vehicle and confirm adequate space is available
LED3000/1 requires 4" x 1.75"
2. Use center-punch if available to start 2 mounting holes and 1 wire exit hole for the 3000/1.
Drill 7/64" mounting holes and 3/8" hole/s for wire exit -
USE THE GASKET PROVIDED AS A TEMPLATE
4. Insert wire through center hole and position mounting screws in holes.
5. Connect **red wire** to power (+) with optional 3A fuse (not provided), and **black wire** to ground (-)
6. Use screws provided to secure LED lamp into position

OPERATION:

1. To select flash pattern touch yellow wire exiting the rear of the unit to red wire 12V (+)
 - a. Hold for less than one second to move to next pattern
 - b. Hold for more than one second to move to previous pattern
 - c. Hold for more than 5 seconds to reset to default (# 1 on carton list)
 - d. See list below for available patterns
2. For sychronized flash patterns
 - a. establish the same pattern on both units (recommended)
 - b. connect the two yellow wires. (Note: lightheads will not sync on random pattern)
3. For alternating flash patterns
 - a. establish the same pattern on both units (recommended)
 - b. connect the two yellow wires
 - c. connect one white wire to power 12V (+) from one of the light heads for alternating display
 - d. for alternating groups of heads one white wire from each light in the group goes to red 12V (+)

FLASH PATTERNS:

- | | |
|-------------------------|----------------------------|
| 0 - Random (Default) | 9 - Single (All) |
| 1 - Single (Split) | 10 - Double (All) |
| 2 - Double (Split) | 11 - Quad (All) |
| 3 - Quad (Split) | 12 - Quint (All) |
| 4 - Quint (Split) | 13 - Mega (All) |
| 5 - Mega (Split) | 14 - Ultra (All) |
| 6 - Ultra (Split) | 15 - Single-Quad (All) |
| 7 - Single-Quad (Split) | 16 - Single H/L (All) |
| 8 - Single H/L (Split) | 17 - Steady 2 (California) |
| | 18 - Steady 4 (All) |



LED3000-X